

SD722W

Speaker Package

Installation Instructions

1. Use two wire nuts to attach the appropriate transformer wires to the field wiring.
See the charts to the right for wire color tap selection.
2. Cut off the bare portion of the unused leads and terminate with wire nuts.

Hardware Reference

Model SD722W mounts to all Atlas Sound 8" baffles except for the FA Series.

Model SD722W is compatible with the following Atlas Sound hardware items:

| | |
|----------------|---|
| Mounting Rings | 75-8, 76-8E2, P77-8, & P78-8 |
| T-Bridges | 81-8R & 81-8S |
| Enclosures | (EZ)95-8 Series, Q408, CS95-8, BMT95-8, & BMT95-8-7 |

Specifications

| | |
|--------------------|--------------|
| Frequency Response | 55Hz – 8kHz |
| Sensitivity | 97dB (1W/1M) |

| Tap Wattage | 70.7V |
|-------------|--------|
| 0.25 | Red |
| 0.5 | White |
| 1 | Yellow |
| 2 | Blue |
| COMMON | BLACK |

| Tap Wattage | 25V |
|-------------|----------------|
| 0.25 | Brown |
| 0.5 | Green w/ White |
| 1 | Violet |
| 2 | Orange |
| COMMON | BLACK |



©2009 Atlas Sound L.P. All rights reserved. Atlas Sound is a trademark of Atlas Sound L.P. All other trademarks are the property of their respective owners. All specs are subject to change without notice. ATS003737 RevA 11/09



1601 JACK MCKAY BLVD.
ENNIS, TEXAS 75119 U.S.A.

TELEPHONE: (800) 876-3333
FAX: (800) 765-3435

AtlasSound.com

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>