

DHT-588BA

Home Theater System

DENON

5.1 Home Theater System featuring AVR-588 HDMI1.3 receiver and Boston Acoustics Horizon MCS 130 speaker system.



Bullet points

AVR-588 Receiver Features

The Latest HD Video Support

- HDMI 1.3a switching*
- Deep Color up to 36-bit and xvYCC broader color space support
- Discrete devices for ultimate HD video performance in each block
- 1080p video pass through

*No audio support

Denon Design Solutions for Maximizing Content Quality

- Identical quality and power for all 7 channels, 75W x 7ch
- Discrete devices for ultimate performance in each block
- New 32-bit floating point DSP
- Minimum signal path design
- Direct Mechanical Ground for stable drive
- Dual power transformer
- Denon customised block capacitor
- Separate unit design

Digital Media Connectivity

- Network Audio/Photo Ready (optional ASD-3N/3W)
- iPod Audio/Photo and Video playback (optional ASD-1R/3N/3W)
- XM Ready

*Shown ASD-3W



Compressed Audio Restorer

Denon's new audio technology for MP3/WMA/AAC compressed audio formats to reproduce higher frequency range and deeper bass sound.

Ease-of-Use

- 3 Quick Select Buttons
- New back panel layout

Boston Acoustics MCS 130 Features

Two way design front and center speakers

- Dual 3 1/2" mid-bass drivers and 1" soft dome tweeter
- Reduced Baffle Diffraction Design for wider, smoother dispersion
- MagnaGuard video shielding
- Adjustable footings
- 5-way gold-plated binding posts
- Built-in wall mount brackets
- Changeable grilles to match your environment (optional)

Two way design surround speaker

- 3 1/2" mid-bass driver
- 1" soft dome tweeter
- Reduced Baffle Diffraction Design for wider, smoother dispersion
- MagnaGuard video shielding
- Adjustable footings
- 5-way gold-plated binding posts
- Built-in wall mount brackets
- Changeable grilles to match your environment (optional)

Matching Subwoofer

- 10" down-firing design
- 200 watt power amplifier
- Deep Channel Design (DCD) for more bass from less amplifier power

Receiver AVR-588 Input / Output terminals

| IN | | | OUT | | |
|-------------------------------|--|-------|-------------------|--|---|
| HDMI | | 2 | HDMI Monitor | | 1 |
| Component | | 3 | Component Monitor | | 1 |
| S-Video | | 3 | S-Video REC | | 1 |
| Composite | | 4 | Monitor | | 1 |
| Analog audio (Tuner included) | | 8 | Composite REC | | 1 |
| Analog EXT. Input | | 7.1ch | Monitor | | 1 |
| Digital OPTICAL | | 2 | | | |
| Digital COAXIAL | | 2 | Analog audio REC | | 2 |
| | | | | | |
| Dock control for iPod | | 1 | Analog Preout | | 1 |
| | | | | | |

AVR-588 Specifications

| Power Amplifier Section | |
|-------------------------|---|
| Rated output | *THD figures are power amp stage values. |
| Front | 75 W +75 W (8 ohms, 20Hz - 20kHz) 110W + 110W (6 ohms, 1kHz) |
| Center | 75 W (8 ohms, 20Hz - 20kHz) 110W (6 ohms, 1kHz) |
| Surround | 75 W +75 W (8 ohms, 20Hz - 20kHz) 110W + 110W (6 ohms, 1kHz) |
| Surround Back | 75 W +75 W (8 ohms, 20Hz - 20kHz) 110W + 110W (6 ohms, 1kHz) |
| General | |
| Power supply | AC 120 V, 60 Hz |
| Dimensions (WxHxD) | 434 x 171 x 377 mm 17-3/32" x 6-47/64" x 14-27/32" |
| Weight | 10.9 kg, 24.0 lbs |

MCS 130 Specifications

| LCR speakers | |
|--------------------|---|
| Nominal Impedance | 8 ohms |
| Dimensions (WxHxD) | 125 x 351 x 103 mm 5" x 13-7/8" x 4-1/16" |
| Weight | 2.27 kg, 5 lbs / each |
| Surround speaker | |
| Nominal Impedance | 8 ohms |
| Dimensions (WxHxD) | 140 x 214 x 102 mm 5-1/2" x 8-7/16" x 4" |
| Weight | 1.36kg, 3 lbs / each |
| Subwoofer | |
| Power supply | AC 120 V, 60 Hz |
| Dimensions (WxHxD) | 419 x 348 x 419 mm 16-1/2" x 13-3/4" x 16-1/2" |
| Weight | 14.15kg, 31.2 lbs |

Accessories

| | | | |
|-------------------|---|-------------------------|---|
| AVR-588 | | MCS 130 | |
| Remote | 1 | Spk ear wires | 5 |
| Batteries | 2 | Pln cable for subwoofer | 1 |
| FM antenna | 1 | Wall mount bracket | 5 |
| AM loop antenna | 1 | | |
| Quick setup sheet | 1 | | |



- Design and specifications are subject to change without notice.
- Dolby and the double-D symbol are registered trademarks of Dolby Laboratories.
- DTS is a registered trademark & the DTS logos and symbol are trademarks of DTS, Inc.
- ©2007 XM Satellite Radio Inc. All rights reserved.

Free Manuals Download Website

<http://myh66.com>

<http://usermanuals.us>

<http://www.somanuals.com>

<http://www.4manuals.cc>

<http://www.manual-lib.com>

<http://www.404manual.com>

<http://www.luxmanual.com>

<http://aubethermostatmanual.com>

Golf course search by state

<http://golfingnear.com>

Email search by domain

<http://emailbydomain.com>

Auto manuals search

<http://auto.somanuals.com>

TV manuals search

<http://tv.somanuals.com>